



Test Report : SHP-10K-55

10KW 3 ψ 3W High Efficiency Digital Power Supply

■ DESIGN VERIFY TEST

Output Function Test

Input Function Test

Protection Function Test

Control Function Test

Component Stress Test

■ SAFETY & E.M.C. TEST

Safety Test

E.M.C. Test


■ RELIABILITY TEST

ENVIRONMENT TEST

■ DESIGN VERIFY TEST

OUTPUT FUNCTION TEST


NO	TEST ITEM	SPECIFICATION	TEST CONDITION	RESULT
1	OUTPUT VOLTAGE ADJUST RANGE	CH1 : 48V~ 57.6 V	I/P : 400VAC I/P : 340 VAC O/P : MIN LOAD Ta : 25°C	36.257V~59.240V /400VAC 36.257V~59.240V/340VAC
2	OUTPUT VOLTAGE(Max) TOLERANCE	V1 : 1%~ -1 %	I/P : 340VAC /530VAC O/P : FULL/ MIN. LOAD Ta : 25°C	V1 : 0.0007 %~ 0 %
3	LINE REGULATION (Max)	V1 : 0.5%~ -0.5 %	I/P : 340VAC~ 530VAC O/P : FULL LOAD Ta : 25°C	V1 : 0 %~ -0.00018 %
4	LOAD REGULATION(Max)	V1 : 0.5%~ -0.5 %	I/P : 400VAC O/P : FULL ~MIN LOAD Ta : 25°C	V1 : 0.00090 %~ 0 %
5	OVER/UNDERSHOOT TEST	< \pm 15%	I/P : 400VAC O/P : FULL LOAD Ta : 25°C	< \pm 15%
6	RIPPLE & NOISE(Max)	V1 : 0.3Vp-p	I/P : 400VAC O/P : FULL LOAD Ta : 25°C	V1 : 145 mVp-p
<div style="display: flex; justify-content: space-around;"> <div style="width: 45%;"> <p>high frequency :</p> </div> <div style="width: 45%;"> <p>low frequency :</p> </div> </div>				
7	SET UP TIME(Max)	400VAC/3000ms	I/P : 400VAC O/P : FULL LOAD Ta : 25°C	2060 ms
<p>INPUT=400VAC/50HZ @ FULL LOAD CH1 : Output Voltage CH2 : AC Input Voltage</p>				



8	RISE TIME (Max)	400VAC/100ms	I/P : 400VAC O/P : FULL LOAD Ta : 25°C	78.2ms
---	-----------------	--------------	--	--------

INPUT=400VAC/50HZ @ FULL LOAD


CH1 : Output Voltage



9	HOLD UP TIME (Typ.)	20ms / 400VAC at full load 25ms / 400VAC at 75% load	I/P : 400VAC O/P : FULL LOAD/75% load Ta : 25°C	400VAC/ 33 ms at full load 400VAC/ 42 ms at 75% load
---	---------------------	---	---	---


INPUT=400VAC/50HZ @ FULL LOAD

CH3 : Output Voltage CH4 : AC Input Voltage




INPUT=400VAC/50HZ @ 75% LOAD

CH1 : Output Voltage CH2 : AC Input Voltage




10	DYNAMIC LOAD	V1 : 5500 mVp-p	I/P : 400VAC O/P : (1)FULL /50% LOAD 50%DUTY / 120HZ (2)FULL /50% LOAD 50%DUTY / 1KHZ	1240mVp-p 1210mVp-p
----	--------------	-----------------	--	------------------------




INPUT FUNCTION TEST

NO	TEST ITEM	SPECIFICATION	TEST CONDITION	RESULT
1	INPUT VOLTAGE RANGE	340VAC~530VAC	(1) I/P : TESTING O/P : FULL LOAD Ta : 25°C	(1) 335 V~530V
			I/P : LOW-LINE-3V=337V HIGH-LINE+10V=540 V O/P : FULL/MIN LOAD (PLEASE CHECK DERATING CURVE) ON : 30 Sec OFF : 30 Sec 10MIN (POWER ON/OFF NO DAMAGE)	TEST : PASS
2	INPUT FREQUENCY RANGE	47HZ ~63 HZ NO DAMAGE	I/P : 340 VAC ~530 VAC O/P : FULL~MIN LOAD Ta : 25°C	TEST : PASS
3	INPUT CURRENT (Typ.)	400V / 11.2 A 480V/ 9.5 A	I/P : 400VAC I/P : 480 VAC O/P : FULL LOAD Ta : 25°C	I =10.96/ 400VAC I =9.13 / 480VAC
4	LEAKAGE CURRENT	< 6.5mA / 530 VAC	I/P : 530 VAC O/P : Min LOAD Ta : 25°C	L1-FG : 5.4mA peak L2-FG : 5.4mA peak L3-FG : 5.4mA peak
5	POWER FACTOR (Typ.)	≥ 0.98 / 400VAC ≥ 0.98 / 480VAC	I/P : 400VAC I/P : 480 VAC O/P : FULL LOAD Ta : 25°C	PF=0.9988 /400VAC PF=0.9964 /480VAC
P.F vs LOAD				



6	EFFICIENCY(Typ.)	94.5%	I/P : 480VAC O/P : FULL LOAD Ta : 25°C	95.08%
---	------------------	-------	--	--------


EFFICIENCY vs LOAD



7	INRUSH CURRENT(Typ.)	40A@400VAC 65A@480VAC COLD START	I/P : 400VAC I/P : 480 VAC O/P : FULL LOAD Ta : 25°C	I = 33.2A/ 400VAC T50=2.38ms I = 43.6A/ 480VAC T50=2.58ms
---	----------------------	--	---	--


INPUT=400VAC/50HZ @ FULL LOAD

CH4 : AC Input Voltage CH3 : Input current



INPUT=480VAC/ 60HZ @ FULL LOAD

CH3 : AC Input Voltage CH4 : Input current



PROTECTION FUNCTION TEST

NO	TEST ITEM	SPECIFICATION	TEST CONDITION	RESULT
1	OVER LOAD PROTECTION	100%~ 105 % PROTECTION TYPE : Constant current limiting, unit will shutdown after 5 sec. re-power on to recover	I/P : 530 VAC I/P : 400VAC I/P : 340VAC O/P : TESTING Ta : 25°C	103.6%/ 530 VAC 103.6%/400VAC 103.6% /340VAC PROTECTION TYPE : Constant current limiting, unit will shutdown after 5 sec. re-power on to recover
2	OVER VOLTAGE PROTECTION	60.5 ~ 69.1V PROTECTION TYPE : Shut down o/p voltage, re-power on to recover	I/P : 530 VAC I/P : 400VAC I/P : 340 VAC O/P : MIN LOAD Ta : 25°C	64.9V/ 530 VAC 64.7V/ 400VAC 64.9 V/ 340VAC PROTECTION TYPE : Shut down o/p voltage, re-power on to recover
3	OVER TEMPERATURE PROTECTION	Protection type : Shut down o/p voltage, recovers automatically after temperature goes down	I/P : 530 VAC I/P : 340 VAC O/P : FULL LOAD	O.T.P. Active Protection type : Shut down o/p voltage, recovers automatically after temperature goes down
4	SHORT PROTECTION	SHORT EVERY OUTPUT 1 HOUR NO DAMAGE	I/P : 530 VAC I/P : 340 VAC O/P : FULL LOAD Ta : 25°C	NO DAMAGE PROTECTION TYPE :

CONTROL FUNCTION TEST

NO	TEST ITEM	SPECIFICATION	TEST CONDITION	RESULT								
1	AUXILIARY POWER (AUX)	Auxiliary voltage output, 11.4~12.6V, referenced to GND-AUX (pin15 & 16). The maximum load current is 1A. This output is not controlled by "Remote ON-OFF" . I/P : 400VAC O/P : FULL LOAD Ta : 25°C Test Result : PASS										
		<table border="1"> <thead> <tr> <th>AUX</th> <th>TOLERANCE</th> <th>RIPPLE</th> <th>TEST RESULT</th> </tr> </thead> <tbody> <tr> <td>12V / 1A</td> <td>11.4~12.6V</td> <td>150mVp-p</td> <td>NoLoad : 12.114V FullLoad : 11.693V Ripple : 27mV</td> </tr> </tbody> </table>			AUX	TOLERANCE	RIPPLE	TEST RESULT	12V / 1A	11.4~12.6V	150mVp-p	NoLoad : 12.114V FullLoad : 11.693V Ripple : 27mV
AUX	TOLERANCE	RIPPLE	TEST RESULT									
12V / 1A	11.4~12.6V	150mVp-p	NoLoad : 12.114V FullLoad : 11.693V Ripple : 27mV									


2 REMOTE ON/OFF CONTROL

4.Remote ON-OFF Control

※ The power supply can be turned ON-OFF by using the "Remote ON-OFF" function.

Between Remote ON-OFF(CN86 pin1) and 5V-AUX(CN86 pin2)	Output Status
Switch close (Short)	power supply ON
Switch open (Open)	power supply OFF

Table 4.1



I/P : 400VAC
 O/P : FULL LOAD
 Ta : 25°C
 Test Result : PASS

Between Remote ON-OFF(CN86 pin1) and 5V-AUX(CN86 pin2)	Output Status
Switch close (Short)	power supply ON
Switch open (Open)	power supply OFF

3 ALARM SIGNAL

5. Alarm Signal Output

※ There are 4 alarm signals, DC-OK, T-ALARM, Fan Fail and AC-OK, in TTL signal form, on CN86. These signals are isolated from output.




Fig 5.1

※ DC OK might mis-triggered when the voltage difference between PSU and the load, please minimized the unnecessary voltage difference.

1. DC OK SIGNAL

High (3.5 ~ 5.5V) : When the $V_{out} \leq 80\% \pm 6\%$.

Low (-0.5 ~ 0.5V) : When the $V_{out} \geq 80\% \pm 6\%$.

The maximum sourcing current is 10mA and only for output.

I/P : 400VAC

O/P : FULL LOAD

Ta : 25°C

Test Result :

Vout	DC OK SIGNAL
$V_{out} \leq 74\%$	5.05V
$V_{out} \geq 86\%$	0V

2. T-ALARM

High (3.5 ~ 5.5V) : When the internal temperature exceeds the limit of temperature alarm.

Low (-0.5 ~ 0.5V) : When the internal temperature is normal.

The maximum sourcing current is 10mA and only for output.(Note)




I/P : 400VAC


O/P : FULL LOAD

Ta : 25°C


Test Result :

PSU STATUS	T-ALARM SPEC	T-ALARM TEST
NORMAL	-0.5 ~ 0.5V	0V
OTP	3.5~5.5V	5.02V

		<p>3. AC OK High (3.5 ~ 5.5V): When AC input $\geq 335 \pm 1.5\%$ Vac, PSU works normally. Low (-0.5 ~ 0.5V): When AC input $\leq 320 \pm 1.5\%$ Vac, PSU shut down. The maximum sourcing current is 10mA and only for output.(Note) I/P : 400VAC O/P : FULL LOAD Ta : 25°C Test Result :</p> <table border="1" data-bbox="643 539 1118 663"> <thead> <tr> <th>AC</th> <th>AC OK SIGNAL</th> </tr> </thead> <tbody> <tr> <td>AC $\leq 320V$</td> <td>0V</td> </tr> <tr> <td>AC $\geq 335V$</td> <td>5.04V</td> </tr> </tbody> </table> <p>4. FAN FAIL High(3.5~5.5V):When the fan fail. Low(-0.5~0.5V):When the fan works normally. The maximum sourcing current is 10mA and only for output.(Note) I/P : 400VAC O/P : FULL LOAD Ta : 25°C Test Result :</p> <table border="1" data-bbox="643 907 1118 1014"> <thead> <tr> <th>FAN</th> <th>AC OK SIGNAL</th> </tr> </thead> <tbody> <tr> <td>Fan works</td> <td>0V</td> </tr> <tr> <td>Fan lock</td> <td>5.03V</td> </tr> </tbody> </table>	AC	AC OK SIGNAL	AC $\leq 320V$	0V	AC $\geq 335V$	5.04V	FAN	AC OK SIGNAL	Fan works	0V	Fan lock	5.03V
AC	AC OK SIGNAL													
AC $\leq 320V$	0V													
AC $\geq 335V$	5.04V													
FAN	AC OK SIGNAL													
Fan works	0V													
Fan lock	5.03V													
<p>4</p>	<p>OUTPUT VOLTAGE PROGRAMMABLE(PV)</p>	<p>1.Output Voltage Programming (or, PV / remote voltage programming / remote adjust / margin programming / dynamic voltage trim) (1)by potentiometer (SVR) (a)Have the DIP switch position-3 set as  (b)Output voltage can be trimmed by SVR. (2)by Output Voltage Programming (a)Have the DIP switch position-3 set as  (b)The output voltage can be trimmed to 50~120% by applying EXTERNAL VOLTAGE between PV+ and PV- on CN53.</p>  <p>Fig1.1</p>												



© The 100% output voltage is 48/115/216/334V.



© The rated current should change with the Output Voltage Programming accordingly.

I/P: 400VAC
 O/P: FULL LOAD
 Ta: 25°C
 TEST RESULT :

MODEL \ PV	1V	5V
SPEC	24V±5%	57.6V±5%
Vout	23.908V	58.74V

5 OUTPUT CURRENT PROGRAMMABLE (PC)

2. Constant Current Programming (or, PC / remote current programming / dynamic current trim)

(1) Default Overload Protection (OLP) value

- (a) Have the DIP switch position-2 set as ON
- (b) Output current is set default value.

(2) by Constant Current Level Programming

- (a) Have the DIP switch position-2 set as ON
- (b) The constant current level can be trimmed to 20~100% of the rated current by applying EXTERNAL VOLTAGE between PC+ and PC- on CN53.




Fig 2.1

※ Under PC function at wattage < 4KW, the power supply might enter burst mode and cause output unstable, please increase the load to minimized the effect.
 ※ Auto de-rating function covered by over temperature protection, it works either in PC mode or under control by communication protocol.

T₁(Typ.): Maximum ambient temperature of full load.
 T₂(Typ.): T₁+5°C.

		<div style="display: flex; justify-content: space-around;"> </div> <p>I/P : 400VAC O/P : TESTING (factory default) Ta : 25°C</p> <table border="1" style="margin-left: auto; margin-right: auto;"> <thead> <tr> <th></th> <th>PC</th> <th>1V</th> <th>5V</th> </tr> </thead> <tbody> <tr> <td>MODEL</td> <td></td> <td></td> <td></td> </tr> <tr> <td>SPEC</td> <td></td> <td>30A±10%</td> <td>133.83A±10%</td> </tr> <tr> <td>lout</td> <td></td> <td>28.85A</td> <td>135.41A</td> </tr> </tbody> </table>		PC	1V	5V	MODEL				SPEC		30A±10%	133.83A±10%	lout		28.85A	135.41A
	PC	1V	5V															
MODEL																		
SPEC		30A±10%	133.83A±10%															
lout		28.85A	135.41A															
6	CURRENT SHARING	CURRENT SHARING TOLERANCE $\pm 10\%$	I/P : 400 VAC O/P : 55V (factory default) 100/50% LOAD Ta : 25°C	O/P : 100% PSU1 : 129 A PSU2 : 128.4 A PSU3 : 131.6 A PSU4 : 135 A O/P : 50% PSU1 : 65 A PSU2 : 65.6 A PSU3 : 69.1 A PSU4 : 67.3 A														

COMPONENT STRESS TEST

NO	TEST ITEM	SPECIFICATION	TEST CONDITION	RESULT
1	PWM Transistor (D to S) or (C to E) Peak Voltage	Q400 Rated : 56A/1200V VGS : -7V~+23V Q401 Rated : 56A/1200V VGS : -7V~+23V	AC ON/OFF I/P : High-Line +3V =533V VDS : VO : 55V O/P : (1)Full Load (2)Output Short (3)Dynamic Load Full Load/ Min. Load 90%Duty/1KHz (4)Dynamic Load Full Load/ Min. Load 90%Duty/3KHz (5)Dynamic Load Full Load/ Min. Load 90%Duty/5KHz	Q400 Q401 VO : 55V VDS: (1) 947.83V (2) 947.83V (3) 947.83V (4) 947.83V (5) 947.83V (6) 963.64V (7) 971.54V

			<p>(6)Dynamic Load 100% Load/ Min. Load 50%Duty/120Hz (7)0%→400% Load.</p> <p><u>VO : 48V</u> O/P : (1)Full Load (2)Output Short (3)Dynamic Load Full Load/ Min. Load 90%Duty/5KHz Ta:25°C</p>	<p><u>VO : 48V</u> (1) 979.45V (2) 947.83V (3) 979.45V</p>	<p><u>VO : 48V</u> (1) 884.58V (2) 868.77V (3) 884.58V</p>
2	P.F.C Transistor (D to S) or (C to E) Peak Voltage	Q165 Rated : 45 A/ 650 V VGS : 22 V / -10V	<p>I/P : High-Line +3V =533V AC ON/OFF <u>VO : 48V</u> O/P : (1)Full Load (2)Output Short (3)Dynamic Load Full Load/ Min. Load 90%Duty/1KHz (4)Dynamic Load Full Load/ Min. Load 90%Duty/3KHz (5)Dynamic Load Full Load/ Min. Load 90%Duty/5KHz (6)Dynamic Load 100% Load/ Min. Load 50%Duty/120Hz (7)0%→400% Load. Ta : 25°C</p>	<p>VDS/IDS : (1) 525.3V / 19.763A (2) 458.1V / 10.672A (3) 521.3V / 15.02A (4) 525.3V / 15.415A (5) 525.3V / 15.415A (6) 513.44V / 15.415A (7) 564.82V / 15.415A</p>	
3	P.F.C DIODE	D163 Rated : 10A/1200V	<p>I/P : High-Line +3V =533V AC ON/OFF <u>VO : 48V</u> O/P : (1)Full Load (2)Output Short (3)Dynamic Load Full Load/ Min. Load 90%Duty/5KHz (4)Dynamic Load 100% Load/ Min. Load 50%Duty/120Hz Ta : 25°C</p>	<p>(1) 947.83V (2) 892.49V (3) 947.83V (4) 884.58V</p>	
4	Diode Peak Voltage	<p>D610 Rated : 130A/200V</p> <p>D613 Rated : 130A/200V</p> <p>D616 Rated : 130A/200V</p> <p>D619 Rated : 130A/200V</p>	<p>AC ON/OFF I/P : High-Line +3V =533V <u>VO : 48V</u> O/P : (1)Full Load (2)Output Short (3)Dynamic Load Full Load/ Min. Load 90%Duty/1KHz (4)Dynamic Load Full Load/ Min. Load 90%Duty/3KHz (5)Dynamic Load Full Load/</p>	<p>D610 : VDS : (1) 154.31V (2) 29.407V (3) 156.68V (4) 140.08V (5) 155.89V (6) 155.89V (7) 76.838V (8) 136.13V</p>	<p>D613 : VDS : (1) 153.52V (2) 28.617V (3) 155.89V (4) 154.31V (5) 155.89V (6) 158.26V (7) 98.972V (8) 140.87V</p>

			Min. Load 90%Duty/5KHz (6)Dynamic Load 100% Load/ Min. Load 50%Duty/120Hz (7)0%→400% Load. (8).NO LOAD Ta : 25°C	D616 : VDS : (1) 162.21V (2) 38.103V (3) 163V (4) 163V (5) 163V (6) 163.79V (7) 113.2V (8) 129.8V	D619 : VDS : (1) 154.31V (2) 29.407V (3) 156.68V (4) 140.08V (5) 155.89V (6) 155.89V (7) 76.838V (8) 136.13V
--	--	--	---	--	---

■ SAFETY& E.M.C. TEST

SAFETY TEST

NO	TEST ITEM	SPECIFICATION	TEST CONDITION	RESULT
1	WITHSTAND VOLTAGE	I/P-O/P : 3.75KVAC/min I/P-FG : 2KVAC/min O/P-FG : 1.25KVAC/min	I/P-O/P : 4.125KVAC/min I/P-FG : 2.4 KVAC/min O/P-FG : 1.5 KVAC/min Ta : 25°C	I/P-O/P : 18.9mA I/P-FG : 14.83mA O/P-FG : 16.19m A NO DAMAGE
2	ISOLATION RESISTANCE	I/P-O/P : 500VDC>100M Ω I/P-FG : 500VDC>100M Ω O/P-FG : 500VDC>100M Ω	I/P-O/P : 500 VDC I/P-FG : 500 VDC O/P-FG : 500 VDC Ta : 25°C	I/P-O/P : 5.82G Ω I/P-FG : 9.18G Ω O/P-FG : 1.57 G Ω NO DAMAGE
3	GROUNDING CONTINUITY	FG(PE) TO CHASSIS OR TRACE < 100 m Ω	40A / 2min Ta : 25°C	28 m Ω

E.M.C TEST

NO	TEST ITEM	SPECIFICATION	TEST CONDITION	RESULT
1	HARMONIC	EN61000-3-2 CLASS A	I/P : 400VAC/50HZ O/P : FULL LOAD Ta : 25°C	PASS
2	CONDUCTION	EN55032 /EN55011 CLASS B	I/P : 400VAC (50HZ) O/P : FULL/50% LOAD Ta : 25°C	PASS
3	RADIATION	EN55032 /EN55011 CLASS A	I/P : 400VAC (50HZ) O/P : FULL LOAD Ta : 25°C	PASS
4	E.S.D	EN61000-4-2 INDUSTRY AIR : 8KV / Contact : 4KV	I/P : 400VAC/50HZ O/P : FULL LOAD Ta : 25°C	PASS
5	E.F.T	EN61000-4-4 INDUSTRY INPUT : 2KV	I/P : 400VAC/50HZ O/P : FULL LOAD Ta : 25°C	PASS

6	SURGE	IEC61000-4-5 INDUSTRY L-N : 2KV L,N-PE : 4KV	I/P : 400VAC/50HZ O/P : FULL LOAD Ta : 25°C	PASS
7	Test by certified Lab & Test Report Prepare Any contradictions of the test results, please refer to the latest EMC test report			

■ RELIABILITY TEST

ENVIRONMENT TEST

NO	TEST ITEM	SPECIFICATION	TEST CONDITION	RESULT
1	TEMPERATURE RISE TEST	MODEL : SHP-10K-55 1. ROOM AMBIENT BURN-IN : 1 HRS I/P : 400VAC O/P : FULL LOAD Ta= 25 °C 2. HIGH AMBIENT BURN-IN : 2 HRS I/P : 400VAC O/P : FULL LOAD Ta= 50 °C		

		NO	Position	ROOM AMBIENT Ta= 25°C	HIGH AMBIENT Ta= 50°C
		1	D163	60.1°C	86.5°C
		2	L5	38.7°C	64.8°C
		3	Q161	60.6°C	86.8°C
		4	Q163	62.8°C	89.4°C
		5	Q165	65.6°C	91.7°C
		6	C173	34.0°C	61.0°C
		7	LF2	26.8°C	49.9°C
		8	L2	24.1°C	48.5°C
		9	C435	40.4°C	67.7°C
		10	Q404	67.1°C	94.0°C
		11	T1 core	55.4°C	83.8°C
		12	T2 core	59.5°C	88.2°C
		13	L40 core	62.5°C	88.9°C
		14	L40 wire	44.1°C	71.3°C
		15	D611	60.3°C	85.0°C
		16	D619	54.3°C	79.3°C
		17	RT61	42.3°C	68.3°C
		18	RT63	42.6°C	68.8°C
		19	RT64	47.7°C	74.2°C
		20	RT65	50.1°C	76.5°C
		21	RTH6	32.9°C	60.2°C
		22	RTH7	50.9°C	78.1°C
		23	C641	36.1°C	63.5°C
		24	T900	33.9°C	60.6°C
		25	Q930	35.3°C	61.9°C
		26	C439	42.2°C	68.5°C
2	OVER LOAD BURN-IN TEST	NO DAMAGE 1 HOUR (MIN)		I/P : 400 VAC O/P : 103%LOAD Ta : 25°C	TEST : OK
3	LOW TEMPERATURE TURN ON TEST	TURN ON AFTER 2 HOUR		I/P : 530VAC/340VAC O/P : 100 %LOAD Ta= -35°C	TEST : OK
4	HIGH HUMIDITY HIGH TEMPERATURE HIGH VOLTAGE TURN ON TEST	AFTER 12 HOURS IN CHAMBER ON CONTROL 50 °C/95 %R.H NO DAMAGE		I/P : 540 VAC O/P : FULL LOAD Ta= 50°C HUMIDITY= 95 %R.H	TEST : OK
5	TEMPERATURE COEFFICIENT	\pm 0.03 %/°C(0~50°C)		I/P : 400 VAC O/P : FULL LOAD	\pm 0.008 %/°C(0~50°C)
6	STORAGE TEMPERATURE TEST	-40~85°C		1. Thermal shock Temperature : -45°C~ +90°C 2. Temperature change rate : 25°C / MIN 3. Dwell time low and high temperature : 30 MIN/EACH 4. Total test cycle : 10 CYCLE 5. Input/Output condition : STATIC	

7	THERMAL SHOCK TEST	-30~50°C	1. Thermal shock Temperature : -35°C~ +55°C 2. Temperature change rate : 25°C / MIN 3. Dwell time low and high temperature : 30 MIN/EACH 4. Total test cycle : 16 CYCLE 5. Input/Output condition : 15cycle:380V/ FULL LOAD AC ON 3sec/AC OFF 1sec TEST 1cycle:380V/ FULL LOAD Burn In Test	
8	VIBRATION TEST	10 ~ 500Hz, 2G 10min./1cycle, 60min. each along X, Y, Z axes	1 Carton & 1 Set (1) Waveform : Sine Wave (2) Frequency : 10~500Hz (3) Sweep Time : 10min/sweep cycle (4) Acceleration : 3G (5) Test Time : 180min in each axis (X.Y.Z) (6) Ta : 25°C	
9	CAPACITOR LIFE CYCLE	SUPPOSE C641 IS THE MOST CRITICAL COMPONENT (1) I/P : 400VAC O/P : FULL LOAD Ta= 25 °C LIFE TIME (2) I/P : 400VAC O/P : FULL LOAD Ta= 50 °C LIFE TIME (3) I/P : 400VAC O/P : 75% LOAD Ta= 50 °C LIFE TIME (4) I/P : 400VAC O/P : 50% LOAD Ta= 50 °C LIFE TIME	(1) 1216239HRS (2) 182052HRS (3) 326009HRS (4) 455538HRS	
10	MTBF	Conducted by Parts Stress Analysis Prediction 281.2K hrs min. Telcordia SR-332 (Bellcore) ; 28K hrs min. MIL-HDBK-217F (25°C)		
11	Ongoing Reliability Test	I/P : 380VAC O/P : FULL LOAD TA=50°C Demonstration Mean Time Between Failure : 50,000 hours		

TEST RESULT	TESTER	REVIEW	APPROVAL
PASS	DANIEL GAO	SANFORD SU	VINCENT TSENG

2020.10.1 TAG-QA-009